

## Programiranje

korak	EVO	MG/SP	
Programski mod	N/A	N/A	EVO: Pritisnite i držite [0] + [INSTALATERSKA ŠIFRA] MG/SP: Pritisni [ENTER] + [INSTALATERSKA ŠIFRA]
Funkcija	[3090]	[703]	Omogući glasovno izveštavanje EVO: [1] Arm/disarm [2] Voice reporting MG/SP: [8] Arm/disarm
Telefonski brojevi	[3091] to [3098]	Master Brzi Meni	EVO:  [3091] Tel. # 1 [3092] Tel. # 2 [3093] Tel. # 3 [3094] Tel. # 4 [3095] Tel. # 5 [3096] Tel. # 6 [3097] Tel. # 7 [3098] Tel. # 8
Omogući brojeve	[3133] to [3833]	N/A	Vezivanje broja za particiju  [3133] Particija 1 [1] to [8] [3233] Particija 2 [1] to [8] [3333] Particija 3 [1] to [8] [3433] Particija 4 [1] to [8] [3533] Particija 5 [1] to [8] [3633] Particija 6 [1] to [8] [3733] Particija 7 [1] to [8] [3833] Particija 8 [1] to [8]
Preskakanje tel.sekretarice	[3052]	[902]	000 do 225 sekundi EVO: Fabrički 008 x 4 = 32 s MG/SP: Fabrički 030 = 30 s
Omogući (PGM)	[3087]	N/A	EVO: Opcija [1] do [8] MG/SP: [1] do [8] uvek omogućeno
Zadržka poruke	[3088]	[836]	000 do 127 seconds
Ponavljanje poruke	[3089]	[837]	000 do 008
Pauza pre sledećeg broja	[3054]	[832]	000 do 255 s
Broj zvonjenja	[3051]	[901]	000 do 008
Maksimalan broj zvanja	[3056]	[831]	000 do 255
Aktiviranje izveštaja	[3090] opt. 3	[804] opt. 8	Aktivirajte Fabrički: OFF

## LED Feedback

Legend		
G = Green	R = Red	<input type="checkbox"/> = Off <input checked="" type="checkbox"/> = On <input type="checkbox"/> = Flashing
LED State	Condition	
ERROR <input checked="" type="checkbox"/>	No data / No EBus*	
ERROR TX <input checked="" type="checkbox"/>	Invalid data	
TX <input checked="" type="checkbox"/>	Sending data	
RX <input checked="" type="checkbox"/>	Receiving data (fast flash)	
RX <input checked="" type="checkbox"/>	Firmware upgrade (flash 2 x sec.)	
ONLINE <input checked="" type="checkbox"/>	Module online / activated	
ONLINE <input type="checkbox"/>	Stand-by mode	
ONLINE <input checked="" type="checkbox"/>	Language upgrade	

P ▲ R ▲ D O X™

## Specifikacije

Kompatibilnost	EVO48 EVO192 EVO96 V1.5 MG Series V2.10 Spectra SP Series V2.10
Potrošnja	35mA
Audio	18,345Hz
Dimenzije	2.5 x 2.5 . (6.4 x 6.4 cm)

